

~~(5) "DIGITAL CABLE TELEVISION BOX" MEANS A DEVICE THAT ACTS AS A TUNER FOR CABLE TELEVISION PROGRAMMING AND CONVERTS DIGITAL SIGNALS RECEIVED FROM A CABLE SERVICE PROVIDER TO A SIGNAL USABLE BY A TELEVISION SET.~~

~~(6) "DIGITAL TELEVISION CONVERTER BOX" MEANS A DEVICE THAT RECEIVES AND DECODES DIGITAL SIGNALS FOR DISPLAY BY AN ANALOG TELEVISION SET.~~

(7) (6) "ILLUMINATED EXIT SIGN" MEANS AN INTERNALLY ILLUMINATED SIGN THAT IS DESIGNED TO BE PERMANENTLY FIXED IN PLACE TO IDENTIFY AN EXIT AND THE BACKGROUND OF WHICH IS NOT TRANSPARENT.

(8) (7) "LARGE PACKAGED AIR-CONDITIONING EQUIPMENT" MEANS PACKAGED AIR-CONDITIONING EQUIPMENT WITH OVER 20 TONS OF COOLING CAPACITY.

(9) (8) (I) "LOW-VOLTAGE DRY-TYPE DISTRIBUTION TRANSFORMER" MEANS A DISTRIBUTION TRANSFORMER THAT:

- (+) 1. HAS AN INPUT VOLTAGE OF 600 VOLTS OR LESS;
- (H) 2. IS AIR-COOLED; AND
- (HH) 3. DOES NOT USE OIL AS A COOLANT.

(II) "LOW-VOLTAGE DRY-TYPE DISTRIBUTION TRANSFORMER" DOES NOT INCLUDE ANY OF THE FOLLOWING TRANSFORMERS:

1. AN AUTOTRANSFORMER IN WHICH THE PRIMARY AND SECONDARY WINDINGS ARE NOT ELECTRONICALLY ISOLATED AND AT LEAST A PORTION OF THE SECONDARY VOLTAGE IS DERIVED FROM THE PRIMARY WINDING;

2. A DRIVE TRANSFORMER DESIGNED ONLY TO PROVIDE POWER TO OPERATE AN ELECTRONIC VARIABLE SPEED MOTOR DRIVE;

3. A GROUNDING TRANSFORMER DESIGNED ONLY TO PROVIDE A SYSTEM GROUND REFERENCE POINT;

4. A HARMONIC TRANSFORMER DESIGNED TO SUPPLY A LOAD WITH A HIGHER THAN NORMAL HARMONIC CURRENT LEVEL AND THAT HAS A K-RATING OF K-4 OR GREATER;

5. AN IMPEDANCE TRANSFORMER THAT HAS A SPECIFIED IMPEDANCE OF LESS THAN 4% OR GREATER THAN 8%;

6. A MACHINE TOOL TRANSFORMER DESIGNED ONLY TO PROVIDE POWER TO MACHINE TOOL EQUIPMENT;

7. A RECTIFIER TRANSFORMER DESIGNED TO PROVIDE POWER ONLY TO A RECTIFIER CIRCUIT AND THAT HAS A NAMEPLATE RATING FOR BOTH THE FUNDAMENTAL FREQUENCY POWER RATING AND THE RMS POWER RATING;